

# Servo amplifier

## mcDSA-E45-SSI

Article number: 1511152



Picture similar

**Technical data**

Supply voltages		Incremental encoder	
Electronic supply voltage Ue* <sup>1</sup>	9..30 V	Type	incremental
Electronic current consumption@ Ue=24V* <sup>2</sup>	typ. 60 mA	Signals	A,/A,B,/B,Inx,/Inx
Power supply voltage Up* <sup>3</sup>	9..60 V	Max. frequency (per channel)	500 kHz
Output current		Input voltage (24V tolerant)	0..5 V
Max. output current	50 A	Signal type	differential, open collector, single ended
Continuous output current @ Up=24V* <sup>4</sup>	10 A	Hall sensors	
Continuous output current @ Up=48V* <sup>4</sup>	8.5 A	Signals	H1,/H1,H2,/H2,H3,/H3
PWM		Max. frequency (per channel)	10 kHz
Output voltage	100% Up	Input voltage (24V tolerant)	0..5 V
PWM frequency	25, 32*, 50 kHz	Signal type	differential, open collector, single ended
Mechanical		Digital inputs	
Size LxWxH	110 x 45 x 77 mm	Number - digital inputs	8 (Din0..7)
Weight	170 g	Low voltage	0..5 V
Environment		High voltage	8..30 V
Protection class	IP20	Digital outputs	
Ambient temperature (operation)	-25..70 °C	Number	2 (Dout0..1)
Ambient temperature (storage)	-25..85 °C	Continuous output current	1.5 A
Rel. humidity (non-condensing)	5..90 %	Load	resistive, inductive
CAN bus		Output voltage	Electronic supply voltage Ue positive switching
Protocol	DS301	Analog inputs	
Device profile	DS402	Number	2 (Ain0..1)
Max. baudrate	1 Mbit/s	Signal type - Ain0	+/- 10 V, 12 Bit, differential
CAN specification	2.0B	Signal type - Ain1	+/- 10 V, 12 Bit, single ended
Galvanically isolated	no		
RS485			
Type	2-Wire EIA-485		
Signals	DATA,/DATA,CLK,/CLK		
Sensor supply (Encoder/Hall/SSI)			
Output voltage	5 V		
Max. output current	0.2 A		

\*<sup>1</sup> No reverse polarity protection, the destruction limit is at overvoltage of >= 33V or short-term peak voltage of 37V < 1s\*<sup>2</sup> power amplifier switched off, 5V output (sensor supply) is free\*<sup>3</sup> No reverse polarity protection, the destruction limit is at overvoltage of >= 80V\*<sup>4</sup> connector cable with max. possible cable cross-section, PWM frequency 32 kHz, ambient temperature 40 °C (t > 40 °C derating), RMS current: 10 A → 8.2 Aeff, 8.5 A → 6.9 Aeff

no guarantee, since value is determined empirical, please consider the application notes to determine the continuous current

\*<sup>5</sup> default value

Additional technical data are available in mcManual.



miControl® GmbH

Chausseestraße 34


14979 Großbeeren (bei Berlin)

Copyright 2024 by miControl® - Modifications and errors excepted

mcDSA-E45-SSI - PV1.13.00.00 / DV1.00.00.00

Web: [www.miControl.de](http://www.miControl.de) e-mail: [info@miControl.de](mailto:info@miControl.de) Tel.: +49 (3379) 312 59-0 Fax: +49 (3379) 312 59-19

## Scheme



©2024 by miControl

## Terminal assignment

X1	Motor	
1	FE	Functional earth
2	+Up	Power supply voltage
3	GND	Ground for power supply voltage
4	Ma	Motor phase A
5	Mb	Motor phase B
6	Mc	Motor phase C
X2	Hall and inc. encoder	
1	H1	Hall sensor 1
2	H2	Hall sensor 2
3	H3	Hall sensor 3
4	A	Inc. encoder, A channel
5	B	Inc. encoder, B channel
6	Inx	Inc. encoder, index channel
7	+U5V	5V output voltage for sensor supply Sensors: encoder, hall
8	/H1	Hall sensor 1 inverted
9	/H2	Hall sensor 2 inverted
10	/H3	Hall sensor 3 inverted
11	/A	Inc. encoder, A channel inverted
12	/B	Inc. encoder, B channel inverted
13	/Inx	Inc. encoder, index channel inverted
14	GND	Ground for sensor supply Notice: don't connect with system GND
X3	I/O's and CAN	
1	+Ue24V	Electronic supply voltage
2	+Ain0	Analog input 0, plus
3	Din0	Digital input 0
4	Din1	Digital input 1
5	Din2	Digital input 2
6	Din3	Digital input 3
7	GND	Ground for electronic supply voltage
8	-Ain0	Analog input 0, minus
9	Dout0	Digital output 0
10	CAN Hi	CAN High
11	CAN Lo	CAN Low
12	CAN GND	CAN Ground

X4	I/O's	
1	Ain1	Analog input 1
2	Din4	Digital input 4
3	Din5	Digital input 5
4	Din6	Digital input 6
5	Dout1	Digital output 1
6	Din7	Digital input 7
X5	Encoder	
1	res.	Reserved
2	res.	Reserved
3	res.	Reserved
4	CLK	SSI clk
5	DATA	SSI data
6	res.	Reserved
7	+U5V	5V output voltage for sensor supply Sensors: encoder, SSI
8	res.	Reserved
9	res.	Reserved
10	res.	Reserved
11	/CLK	/SSI clk
12	/DATA	/SSI data
13	res.	Reserved
14	GND	Ground for sensor supply Notice: don't connect with system GND